

Shrouded Power Relay F4 A

- Pin assignment similar to ISO 7588 part 1
- Plug-in terminals
- Customized versions on request
 - Integrated components (e.g. resistor, diode)
 - Customized marking/color
 - Special cover with bracket

Typical applications

Cross carline up to 40A for example: ABS control, blower fans, cooling fan, energy management, engine control, fuel pump, heated front screen, lamps: front, rear, fog light, main switch/supply relay, wiper control.

Contact Data

eonaor Buta				
Contact arrangement	1 form A, 1 NO	1 form C, 1 CO		
Rated voltage	12VDC	12VDC		
Limiting continuous current	NO	NO/NC		
23°C, form A/form B	60A	60/45A		
85°C, form A/form B	40A	40/30A		
125°C, form A/form B	17A	17/12A		
Limiting making current ¹⁾				
form A/form B	120A	120/45A		
Limiting breaking current,				
form A/form B	60A	60/40A		
Limiting short-time current				
overload current, ISO 8820-3 ²⁾	1.35 x 40A, 1800s			
	2.00 x 40A, 5s			
	3.50 x 40A, 0.5s			
	6.00 x 4	0A, 0.1s		
Jump start test, ISO 16750-1		for 5min,		
	U	inal current at 23°C		
Contact material		based		
Min. recommended contact load ³⁾	1A at 5VDC			
Initial voltage drop at 10A,				
form A (NO), typ./max.	15/200mV	15/200mV		
form B (NC), typ./max.	-	20/250mV		
Frequency of operation at nominal lo				
Operate/release time typ.		ms ⁴⁾		
Electrical endurance	>1x10 ⁵ ops	>1x10 ⁵ ops		
resistive load, NO contact	40A, 14 VDC	40A, 14 VDC		

Max. DC load breaking capacity



Load limit curve 1: arc extinguishes during transit time (changeover contact). Load limit curve 2: safe shutdown, no stationary arc (make contact). Load limit curves measured with low inductive resistors verified for 1000 switching events.

02-2017, Rev. 0217 www.te.com © 2017 TE Connectivity Datasheets and product specification according to IEC 61810-1 and to be used only together with the 'Definitions' section.



F136_fcw3c_bw

Contact Data (continued)

 Mechanical endurance
 >1x10⁶ops

 1) The values apply to a resistive or inductive load with suitable spark suppression and at maximum 14VDC for 12VDC or 28VDC for 24VDC load voltages. For a load current duration of maximum 3s for a make/break ratio of 1:10.

duration of maximum 3s for a make/break ratio of 1:10.2) Current and time are compatible with circuit protection by a typical automotive fuse. Relay will make, carry and break the specified current.

 See chapter Diagnostics of Relays in our Application Notes or consult the internet at http://relays.te.com/appnotes/

4) For unsuppressed relay coil. A low resistive suppression device in parallel to the relay coil increases the release time and reduces the lifetime caused by increased erosion and/or higher risk of contact tack welding.

Coil Data

Rated coil voltage

Coil versions, DC coil

	,				
Coil	Rated	Operate	Release	Coil	Rated coil
code	voltage	voltage	voltage	resistance ⁵⁾	power ⁵⁾
	VDC	VDC	VDC	Ω±10%	W
001	12	7.2	1.6	114	1.3

12VDC

5) Without components in parallel.

All figures are given for coil without pre-energization, at ambient temperature +23°C.

Coil operating range



Does not take into account the temperature rise due to the contact current $\mathsf{E}=\mathsf{pre}\text{-}\mathsf{energization}.$

Datasheets and product data is subject to the terms of the disclaimer and all chapters of the 'Definitions' section, available at http://relays.te.com/definitions

Datasheets, product data, 'Definitions' section, application notes and all specifications are subject to change. 1



Shrouded Power Relay F4 A (Continued)

Insulation Data		
Initial dielectric strength		
between open contacts	500V _{rms}	
between contact and coil	500V _{rms}	
between adjacent contacts	500V _{rms}	
Load dump test		
ISO 7637-1 (12VDC), test pulse 5	V _s =+86.5VDC	
ISO 7637-2 (24VDC), test pulse 5	V _s =+200VDC	

Other Data

compliant
JL94 HB or better ⁶⁾
-40 to 125°C
6 cycles, storage 8/16h
10 cycles, -40/+85°C (5°C/min)
6 cycles, upper air temp. 55°C
Ca 56 days
RT III – sealed
IP67 (sealed)
only with special connector
10±2cm ³ /m ³ SO ₂ , 10 days
1±0.3cm ³ /m ³ H ₂ S, 10 days
10 to 500Hz, min. 5g ⁷⁾
11ms, min. 20g ⁷⁾
1m onto concrete

Other Data (continued) Terminal type	plug-in, QC
Cover retention	pidg in, do
pull force	150N
push force	200N
Terminal retention	
pull force	100N
push force	100N
Weight	approx. 60g (2.1oz)
Packaging unit	108 pcs.
6) Refers to used materials.	

No change in the switching state >10µs. Valid for NC contacts, NO contact values significantly higher.

Accessories

For fitting connectors please contact us via online Support Center

Terminal Assignment

NOR 1 form A, NO with resistor





1 form C, CO with resistor

COR

2

Datasheets and product specification ac-cording to IEC 61810-1 and to be used only together with the 'Definitions' section.

Datasheets and product data is subject to the terms of the disclaimer and all chapters of the 'Definitions' section, available at http://relays.te.com/definitions

Datasheets, product data, 'Definitions' sec-tion, application notes and all specifications are subject to change.



Automotive Relays Plug-in Mini ISO Relays

Shrouded Power Relay F4 A (Continued)

Dimensions





View of the terminals (bottom view)





Prod	uct co	ode structure			Typical pro	oduct code	V23136	-A	1	001	-X057
Туре											
	V231	36 Power Relay F4 A									
Conta	ct arra	angement									
	Α	1 form C, 1 CO	В	1 form A, 1 NO							
Cover											
	1	Bracket at terminal 3									
Coil											
	001	12VDC									
Termi	nal/arr	angement									_
		Customized (nnn: version number)									

Product code	Arrangement	Cover	Coil suppr.	Circuit ¹⁾	Coil	Cont. materia	I Terminals	Part number
V23136-A1001-X057	1 Form C, 1 CO	Shrouded	Resistor 680Ω	COR	12VDC	Silver based	Plug-in, QC	1-1414552-0
V23136-B1001-X051	1 Form A, 1 NO			NOR				1-1414121-0
1) 0 +	-!!				•	•		•

1) See terminal assignment diagrams.

Other types on request. This list represents the most common types and does not show all variants covered by this datasheet.

Datasheets and product specification ac-cording to IEC 61810-1 and to be used only together with the 'Definitions' section.

Datasheets and product data is subject to the terms of the disclaimer and all chapters of the 'Definitions' section, available at http://relays.te.com/definitions

Datasheets, product data, 'Definitions' sec-tion, application notes and all specifications are subject to change.

3

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

TE Connectivity: V23136A1001X057